

AMP03



PRESENTATION

AMP03 is an amplifier/mixer designed for paging, music, and sound reinforcement applications in P.A. systems.

FEATURES

30W AMPLIFIER Proel AMP03 is a mixer amplifier designed to allow microphone announcements and music programs diffusion in all PA applications. Main features - Two microphone inputs unbalanced with 6,3 mm - One Aux input and One Phone which can be rear switched - Power led indicator - Main volume control - AUX/PHONO volume control - MIC1 volume control - MIC2 volume control - Low, medium & high volume control - Ground terminal connector - Four outputs amongst which three are at constant impedance (4/8/16 ohm) and one at constant voltage (100V) - MIC1 input with priority function, apt to receive the microphone stand BM100 (stand to be used with an adaptor and eventual chime circuit)

CODE: PA AMP03



TECHNICAL SHEET

Output power RMS / MAX:30/45W

Inputs:2x MIC unbalanced, 1x PHONO, 1x AUX

Input Sensitivity:MIC: 2mV / 5 Kohm (MIC1 with priority)

Controls:1 MAIN VOLUME CONTROL

Loudspeakers outputs:100V - 4/8/16 ohm

Frequency response:65Hz - 18KHz (-3dB)

Distortion (THD):

S/N Ratio:> 55dB

Power Supply:230Vac 50Hz

Operating temperature:0 - 40°C

Input/Output Connectors:MIC: 2x JACK 6.3mm

Dimensions (W x H x D):320 x 80 x 190mm

Weight:4,5
